The ATLAS Level 2 Trigger

Maris Abolins

Michigan State University

28-Nov-1996



Outline

- Trigger Overview
- Physics Challenges
- Level 2 Guidelines
- Longterm Strategy
- The Demonstrator Program
  - Demonstrator A
  - Demonstrator B
  - Demonstrator C
  - Common Activities
  - Modelling and Simulation
  - Hybrid Solutions
- Conclusions



Trigger System Overview



Readout Buffers

- After a LVL1 accept, data are moved through a Readout Driver into an ATLAS standard Readout Buffer (ROB)
- The data are held in the ROB during LVL2 decision
- The data are moved to the LVL3 farm on receipt of a LVL2 accept



ATLAS

Level 2 Trigger

- Works with data at full granularity
- Uses the Region of Interest (RoI) principle
  - LVL1 supplies RoI information
  - LVL2 transfers small fraction of data (~few %)
- Processing
  - Local - Feature extraction from sub-detectors
  - Global - Combine features



ATLAS



Regions of Interest

Regions of Interest (RoI)



ATLAS

M. Abolins, CERN 28-Nov-1996

Regions of Interest

- Number of RoI's
  ATLAS jet generation, 35 GeV threshold, $|\eta| \leq 3$
  - $\geq$ 5 GeV isolated em clusters = 2.6 average
  - $\geq$ 6 GeV no isolation (em) = 3.7 average
- RoI size
  - calorimeter - em cluster $\Delta\eta x \Delta\phi = 0.5x05$
    --> 0.6% of total calorimeter area
  - SCT- size increased by z vertex spread
    -->1 - 4% of total Inner Detector area
- RoI Data Volume ~few % of total data volume
- Mapping of data onto ROB's may increase fraction

System	RoI Size (kB)	Rate to L2 (GB/S)	Total Rate (GB/s)
SCT + pixels	1.0	0.3	21
TRT	3.5	1.0	50
Calo.	2.5	0.7	35
Muon	1.0	0.3	20
TOTAL		2.3	131



RoI's continued

- Primary RoI's - those RoI's responsible for the LVL1 trigger
- Other RoI's
  - LVL1 tagged e.g. lower calorimeter thresholds
  - generated by Level 2 in sequential processing



Triggering Principles

- Level 1
  - 1% Deadtime
  - Pipelined
  - Uses custom hardware with fixed algorithms and programmable parameters
- Level 2 - to be determined
- Level 3
  - A farm of commercial processors
  - Running “offline” code



Examples of Physics Signatures
$\mathcal{L} = 10^{34}\text{cm}^{-2}\text{s}^{-1}$

Process	Level-1	Level-2 (I = isolated)
$H^0 \rightarrow \gamma\gamma$	$\geq$ 2 em, E_T > 20 GeV	2 γ, E_T > 20 GeV
$H^0 \rightarrow ZZ^* \rightarrow$ $l^+ l^- l^+ l^-$	$\geq$ 2 em, E_T > 20 GeV $\geq 2\mu$, p_T > 6 GeV $\geq$ 1 em, E_T > 30 GeV $\geq 1\mu$, p_T > 20 GeV	2 e, E_T > 20 GeV 2 μ, E_T > 6 GeV, I 1 e, E_T > 30 GeV 1 μ, E_T > 20 GeV, I
$(Z \rightarrow l^+ l^-) + X$	$\geq$ 2 em, E_T > 20 GeV $\geq 2\mu$, p_T > 6 GeV $\geq$ 1 em, E_T > 30 GeV $\geq 1\mu$, p_T > 20 GeV	2 e, E_T > 20 GeV 2 μ, E_T > 6 GeV, I 1 e, E_T > 30 GeV 1 μ, E_T > 20 GeV, I
$t\bar{t} \rightarrow$ leptons + jets	$\geq$ 1 em, E_T > 30 GeV $\geq 1\mu$, p_T > 20 GeV	1 e, E_T > 30 GeV 1 μ, E_T > 20 GeV, I
$W', Z' \rightarrow$ jets	$\geq$ 1 jet, E_T > 150 GeV	1 jet, E_T > 300 GeV
SUSY $\rightarrow$ jets $\rightarrow E_T^{miss}$	$\geq$ 1 jet, E_T > 150 GeV E_T^{miss} >150 GeV	3 jet, E_T > 150 GeV E_T^{miss} >200 GeV

l, γ for $|\eta| < 2.5$; Jets for $|\eta| < 3.$; Missing E_T for $|\eta| < 5$; RoI's on all $e/\gamma > 10$ GeV & μ's > 6 GeV p_T.

ATLAS



M. Abolins, CERN 28-Nov-1996

Trigger Rates - Level 1

Trigger selection	Rate at $\mathcal{L} = 10^{34}$ cm^{-2} s^{-1}
Single muon, ≥ 1 μ, $p_T \geq 20$ GeV	4 kHz
Single e.m. cluster, $E_T \geq 30$ GeV, e.m. and hadronic isolation	20 kHz
Double muon, ≥ 2 μ ,$p_T \geq 6$ GeV	1 kHz
Double e.m. cluster, $E_T \geq 20$ GeV, e.m. and hadronic isolation	4 kHz
Single jet, ≥ 1 jet, $p_T \geq 150$ GeV	3 kHz
$E_t^{miss} > 150$ GeV	1 kHz
other triggers	5 kHz
Combined rate	**~38 kHz**

ATLAS



Expected LVL2 trigger rates (TP)

indicative rates for inclusive selections

Trigger selection	**Rate at $\mathcal{L} = 10^{34}$ cm^{-2} s^{-1}**
Isolated muon, ≥ 1 μ, $p_T \geq 20$ GeV, single muon, ≥ 1 μ, $p_T \geq 40$ GeV	0.2 kHz 0.1 kHz
Single electron, ≥ 1 e $E_T \geq 30$ GeV, single gamma, ≥ 1 γ $E_T \geq 60$ GeV	0.3 kHz 0.1 kHz
Isolated di-muon, ≥ 2 μ ,$p_T \geq 6$ GeV double muon, ≥ 2 μ ,$p_T \geq 10$ GeV	0.1 kHz 0.08 kHz
Di-electron or di- gamma, $p_T \geq 20$ GeV,	0.2 kHz
Single jet, ≥ 1 jet, $p_T \geq 300$ GeV	0.1 kHz
$E_T^{miss} > 200$ GeV	0.1 kHz
other triggers	0.1 kHz
Combined rate	**~1.4 kHz**

ATLAS



Expected LVL2 Inclusive rates at Low Luminosity (TP)

Trigger selection	Rate at $\mathcal{L} = 10^{33}\,cm^{-2}\,s^{-1}$
B-physics Level-2 triggers, single muon, $\geq 1\ \mu$, $p_T \geq 20$ GeV	0.8 kHz 0.2 kHz
Single electron, ≥ 1 e $p_T \geq 20$ GeV, single gamma, $\geq 1\ \gamma$ $p_T \geq 40$ GeV	0.2 kHz 0.06 kHz
Dual electron, ≥ 2 e $p_T \geq 15$ GeV, dual gamma, $\geq 2\ \gamma$ $p_T \geq 20$ GeV	0.01 kHz 0.01 kHz
Single jet, ≥ 1 jet, $p_T \geq 200$ GeV three jet, ≥ 3 jet, $p_T \geq 100$ GeV	0.06 kHz 0.02 kHz
$E_T^{miss} > 200$ GeV	0.01 kHz
Prescaled triggers	0.1 kHz
Combined rate	**~1.5 kHz**

ATLAS



More recent Trigger Menu Studies can be found in DAQ-NO-54

Rates for B-physics (TP)

Trigger selection	Rate at $L = 10^{33}$ cm^{-2} s^{-1}
Level-1 single muon, $p_T \geq 6$ GeV	8000 Hz
Level-2 single muon, $p_T \geq 6$ GeV	4000 Hz
Additional Level-2 requirements	
second muon, $p_T \geq 5$ GeV	56 Hz
electron, $p_T \geq 5$ GeV	112 Hz
electron pair, $p_T \geq 1$ GeV	400 Hz
hadron pair, $p_T(h) \geq 6$ GeV with $p_T(\text{pair}) \geq 15$ GeV	100 Hz
$D_S^{\pm} \rightarrow \phi\pi^{\pm} \rightarrow K^+K^-\pi^{\pm}$ with $p_T \geq 1$ GeV and loose mass cuts	160 Hz
Combined rate	**~830 Hz**

ATLAS



Level-2 Processing

- Algorithms only: no preprocessing or system overhead
- Calorimeter
  peak find and shape analysis - 100 μs @500 mips
- Continuous Tracking (TRT)
  histogramming method - 600 μs @500 mips
- Precision Tracking
  histogramming method - 800 μs @500 mips
- Muon (2 step process)
  - Pattern recognition
  - p_T calculation

100 μs with non-optimised code



Motivation for Sequential Processing



Total Number of RoI's



No. of "Trigger" RoI's

Luminosity	Low	High
Thrshld (Gev)	20	40
Calo alone	3	10
Calo +Track	25	60

Background Rejection Factor at 90% eff. for em Trigger RoI's

- Only 1.2 Trigger RoI's for 4.7 L1 "objects"
- Only 10%-20% of Trigger RoI's survive first step
- Tracking algorithms are slower by x 10

Algorithm	Proc. time
Calor	50-100 μsec
Muon	< 100 μsec
Track	500-5000 μsec

Timing Benchmarks for Selected Algorithms

500 Mips processors

Suggested Procedure:

•Confirm Trigger RoI's using Calorimeter and Muon alone

•Do track finding only if necessary

ATLAS



Strategy Meeting (Cosener's House, June '95)

- Decision made to produce User Requirement Document (URD)
- Establish Milestones
  - Architectural Choice e.g.
    - data driven elements vs multiple farms
    - control via network or separate lines
    - algorithmic complexity
    - "push" (data transfer initiated by source node) or "pull" (data transfer initiated by target node)
  - Technological Choice e.g.
    - switch and data concentrator technology
    - farm technology
    - network technology



Demonstrator Program

- Why
  - Explore architectural options
  - Explore technical options
  - Optimize choice financially and technologically
  - Time and expertise on hand
- Common Yardstick
  - 100 kHz operation
  - Demonstration of scalability to full detector
  - User Requirement Document
- Task Force Decision
  - Three Demonstrators (A, B, C)
  - Mix architectural and technological considerations in a single demonstrator program



Interim Milestones (to be updated)

- **Sep 1997** - Major Architecture Choices Made
- **Dec 1997**-T/DAQ Technical Proposal Due
- **Jul 1998** - Major Technology Choices Made
  Small-Scale Prototype (SSP) Defined
- **Jul 1999** - SSP assembled
- **Jan 2001** - Full-chain prototype (FCP) defined
- **Jan 2002** - FCP accepted
- **Jan 2003** - Commissioning of LVL2
- **Jul 2003** - Integration of LVL2 with rest of T/DAQ
- **Jan 2004** -Integration of LVL2 with subdetectors
- **Jan 2005** - Run with cosmic rays
- **Jul 2005** - Full Level-2 ready for collisions



Demonstrator Participants

Overall Coordinator: Fred Wickens

- Demonstrator "A" -
  - Coordinator: Prof. Reiner Maenner
  - Institutes: Cracow, Heidelberg, Jena, Mannheim, Weizmann
- Demonstrator "B"
  - Coordinator: John Renner Hansen
  - Institutes: Argonne, CERN, NBI(Copenhagen), Cracow, Edinburgh, JINR, Lecce, Liverpool, Manchester, Michigan State, NIKHEF, Oxford, RAL, RHBNC, UFRJ(Rio), Rome INFN, Valencia, UCL
- Demonstrator "C"
  - Coordinator: Patrick Le Du]
  - Institutes: Argonne, CERN, Michigan State, Oxford, Rome, Lecce, Saclay, Prague



L2 Architecture “A”



- Optimized for Fast Feature Extraction (FPGA). Based on Enable++.
- Operates in Push Mode

ATLAS



Architecture A

Potential advantages

- "On the fly" RoI collection
- Feature Extraction at 100 kHz. Typical FPGA execution times: 10 μs. Minimal latency
- Smaller system
- Simplified supervision and control

Possible problems

- Algorithmic complexity may be limited → higher output rates
- May be difficult to combine detectors with different geometries e.g. barrel and endcap
- Sequential processing probably ruled out



Critical Demonstrations for Architecture A

- In parallel collection of several RoI's in a given subdetector at 100 kHz
- Data-driven feature extraction for all detectors at 100 kHz
- Demonstration of satisfactory algorithmic adaptability to different luminosity conditions, changing run requirements and to evolving physics demands
- Event synchronization



Demonstrator A
Hardware Layout

Goal: RoI collection and FEX @ 100 kHz



1 Slate = 1 ROB Crate or input from preceeding RoIC

SLATE is a fast data emulation device

ATLAS



M. Abolins, CERN 28-Nov-1996

L2 Architecture B
Data Flow Diagram



- Optimized for parallel processing of RoI's and detectors
- Operates in push mode
- This is the Technical Proposal Design
- The two networks shown may be partitions of the same network

ATLAS

Architecture B

Potential Advantages

- Flexibility inherent in general purpose processors
- Lower latency from parallel processing and data flow

Possible Problems

- Sequential processing presents challenges
  - logic control
  - latency issues
- More processing power may be needed

Critical Demonstrations

•Achieve complete RoI collection at 100 kHz. Involves ROB's, supervisor and network interacting with feature extraction (FEX) processors.

•Feature extraction can be done for all detectors within local network bandwidth limits and financial constraints.

•Supervisor functioning at full rate.

•Sequential processing control paths and performance at full bandwidth. Event synchronization.



Demonstrator B2



ATLAS

M. Abolins, CERN 28-Nov-1996

L2 Architecture C



- Optimized for sequential processing of RoI's
- Operates in pull mode
- Distinction between Level 2 and Level 3 disappears

ATLAS



The Single Farm Idea



Main features

- Integration of data and protocol networks
- Pull data flow control strategy
- Single processor per event
- Several events per processor

ATLAS



Architecture C

Potential Advantages

- Well adapted to sequential processing
- Destination can also be Event Builder and Level 3 processor

Possible Problems

- Data and control traffic on same switch
- Multiple events per processor

Critical Demonstrations

•Data and control traffic patterns are within network capabilities.

•Complete RoI collection can be achieved.

•Data concentrators do not impede data flow



Demo C for Testlab



Common Areas for Demonstrators

- Base-line definitions of
  - detectors
  - data formats
  - ROB/RoI sizes
  - algorithms
  - data samples
- Common hardware and software
  - ROB's
  - Supervisor
- Modelling and Emulation
- Performance Measurements



Level 2 Supervisor



TASKS

STEWARD: Manages (frees and reviews usage of) local and global processors

ROI Router: dispatches ROI information to CPU's

CPU's: determine appropriate free local/global processors to use and determine buffers to request data from and assemble request packet

ROB Router: routes buffer requests to appropriate crates (A&B only)

ATLAS



Modelling and Simulation

- Paper Models
  - Inputs
    - Full Trigger Menus
    - Average Numbers of RoI's
    - Average processing times, overheads, circuit delays etc.
  - Output
    - Number of processors needed
    - Switching bandwidth needed
    - Link occupancy
    - Overall latency
  - Does not model
    - Possible queueing problems
    - Data flow fluctuations
  - Initial studies for Model C at Saclay
    now A & B also modelled.
- Modsim II and C++ Studies underway



Paper Model - Architecture C



ATLAS

M. Abolins, CERN 28-Nov-1996

Paper Model Diagram
Architecture B



ATLAS

M. Abolins, CERN 28-Nov-1996

Hybrid Solutions

- We are actively examining the relative merits of general purpose versus FPGA processors for specific high intensive computing tasks.

- Both architecture B and architecture C are considering FPGA processors for full TRT scans and for b-jet scans of the SCT.



Questions and Conclusions

- Questions
  - Is sequential processing necessary?
  - Are secondary RoI's necessary?
  - Does missing E_T need to be recalculated at Level 2?
  - Do we need a full TRT scan at Level 2?
  - Do we need b-jet tag at Level 2?
  - How is the LVL2/LVL3 boundary defined?
  - Do we need preprocessing?
- Conclusions
  - A robust and comprehensive demonstrator program is underway
  - Efforts are being made to integrate elements of the separate architectures for an optimal design
  - Prospects are good for a Level 2 that will be optimized in price and performance and that will benefit from technological innovations in the commercial sector