Surface Mount

RF Transformer

0.05 to 200 MHz


Maximum Ratings

Operating Temperature	-20°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power	250mW
DC Current	30mA
Pormonant damage may eccur if any	of those limits are evenedo

Pin Connections

4
6
5
3
1
2


Outline Drawing



Outline Dimensions (inch)

F	E	D	C	B	A
. 020	. 042	. 010	. 23	. 27	. 30
0.51	1.07	0.25	5.84	6.86	7.62
wt	L	K	J	H	G
grams	.036	.31	.09	.05	.100
0.50	0.91	7.87	2.29	1.27	2.54

Config. B



Features

- wideband, 0.05 to 200 MHz
- · good return loss
- also available with surface mount gull wing (KK81) plug-in (X65) leads

Applications

- HF/VHF
- · impedance matching
- balanced antennas



CASE STYLE: W38 PRICE: \$5.95 ea. QTY (1-9)

+ RoHS compliant in accordance with EU Directive (2002/95/EC)

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications.


Transformer Electrical Specifications


Ω RATIO (Secondary/Primary)	FREQUENCY (MHz)	INSERTION LOSS*		
		3 dB MHz	2 dB MHz	1 dB MHz
3	0.05-200	0.05-200	0.2-50	1-30

* Insertion Loss is referenced to mid-band loss, 0.4 dB typ.

Typical Performance Data

FREQUE (MH:		I INPUT R. LOSS (dB)	
0.05	5 2.88	1.46	
0.10	1.29	4.13	
0.20	0.58	8.81	
0.50	0.39	15.77	
1.00	0.36	19.03	
30.00	0.51	11.31	
50.00	0.91	7.28	
100.86	1.96	3.92	
195.15	2.78	3.87	
200.00	2.76	4.08	





For detailed performance specs

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minicipouits.com IF/RF MICROWAVE COMPONENTS